



# LED Video Light



Instruction manual | 说明手册  
Chinese English Bilingual | 中英文双语

Model: LED 36

## Foreword:

Thank you for purchasing this Godox Product!

LED36 video light is excellent for macrophotography, product shooting, and video recording, etc. This lightweight and portable light provides high brightness and accurate color temperature. You can flexibly control the light brightness by using the dimmer and by interlocking multiple lights.

## Warning:

- ⚠ Always keep this product dry. Do not use in rain or in damp conditions.
- ⚠ Do not disassemble. Should repairs become necessary, this product must be sent to an authorized maintenance center.
- ⚠ Keep out of reach of children.
- ⚠ As this product do not have waterproof function, please take measures of waterproof in rainy or damp environment.
- ⚠ Do not use or store the product if the ambient temperature reads over 50°C.
- ⚠ Do not use the flash unit in the presence of flammable gases, chemicals and other similar materials. In certain circumstance, these materials may be sensitive to the strong light emitting from this flash unit and fire or electromagnetic interference may result.
- ⚠ Observe precautions when handling batteries
  - Do not put batteries into a fire or apply direct heat to them.
  - Batteries are prone to leakage when fully discharged. To avoid damage to the product, be sure to remove batteries when the product is not used for a long time or when batteries run out of charge.
  - Should liquid from the batteries come into contact with skin or clothing, rinse immediately with fresh water.

## Parts:

- 01. 36 LED Beads
- 02. Power Switch
- 03. Brightness Controller
- 04. Battery Compartment
- 05. Light Hotshoe Connection
- 06. Locking Ring A
- 07. Locking Ring B
- 08. Camera Hotshoe Connection
- 09. 1/4" Bracket Mounting Hole



## Installation and Operation

### 1.Installing the Video Light

- Screw the Locking Ring A (06) and B (07) to the highest point so that the light is fixed and insert the Camera Hotshoe Connection horizontally into the hotshoe of a camera or a camcorder.
- Tighten the Locking Ring B (07).



Note: If your camcorder has no hotshoe connection, you are advised to purchase a connecting bracket for camcorder. The video light has a 1/4" Bracket Mounting Hole as your camcorder does. Therefore, you can easily connect both the light and the camcorder to the bracket.

### 2.Using the Video Light



- Open the Battery Compartment (04).



- Install batteries (2\*AA) according to indications in the compartment and then close it.



- Switch the power on, the video light giving out light.



- Turn the Brightness Controller (03) to adjust the brightness.

Turn the power off if it will not be used.

### 3.Interlocking Multiple Video Lights

Through the Light Hotshoe Connection (05) and Camera Hotshoe Connection (08), multiple video lights can be interlocked together to strengthen the lighting brightness and get a better control of the lighting effects.



## Technical Data:

Battery	Two AA batteries
Power	<1.3W
Duration	Approx. 1.5 hours with alkaline batteries
Color Temperature	5500~6500K
Brightness	>260Lux (0.5m)
Brightness Control	Stepless
LED Beads Quantity	36
Operation Temperature	-10~40°C
Dimension	70*89*38mm
Net weight	80g

\* Product design and specifications are subject to change without notice.